





TForce Core LED HPL 18W E27 827 FR

Philips TrueForce Core LED HPL lamps are an easy, LED solution with a short payback to replace High Intensity Discharge (HID) lamps. This new generation of LED Core Post–Top lamps brings all the energy–efficiency and long-lifetime benefits of LED to HID replacement, while delivering instant saving for a low initial investment. Furthermore, TrueForce CorePro LED HPL lamps are designed to have the same lamp size and light distribution as their HID alternatives. And thanks to our high-power LED filament technology, you'll never know the difference. Plus, their unique IP65 design means that TrueForce Core LED HPL Post–Top lamps can be used for outdoor, as well as indoor applications.

Warnings and Safety

• Installation should always be performed by a qualified electrician or installer. Use the installation guide for instructions.

Product data

| General Information | | |
|----------------------------|--------------------|--|
| Cap-Base | E27 | |
| Nominal lifetime | 25,000 hour(s) | |
| Switching Cycle | 50,000 | |
| Lighting Technology | LED | |
| Flux measurement reference | Sphere | |
| CE mark | Yes | |
| EU RoHS compliant | Yes | |
| | | |
| Light Technical | | |
| Color Code | 827 [CCT of 2700K] | |
| Beam Angle (Nom) | 330 degree(s) | |
| Luminous Flux | 2,600 lm | |
| | | |


| Color Designation | Warm White (WW) |
|--|-----------------|
| Correlated Color Temperature (Nom) | 2700 K |
| Luminous Efficacy (rated) (Nom) | 144 lm/W |
| Color Consistency | <6 |
| Color rendering index (CRI) | 80 |
| LLMF At End Of Nominal Lifetime (Nom) | 70 % |
| Flickering value (PstLM) - Flickering value as per | 1 |
| EN 61000-3-3 | |
| Stroboscopic effect visibility measure (SVM) | 3.3 |
| Photobiological safety according to EN 62471 | RG1 |
| | |
| Operating and Electrical | |
| Input Frequency | 50 to 60 Hz |
| | |

Datasheet, 2024, March 18 data subject to change

| Power Consumption | 18 W |
|--|---------------|
| Lamp Current (Nom) | 129 mA |
| Starting Time (Nom) | 0.5 s |
| Warm-up time to 60% light | 0.5 s |
| Power Factor (Fraction) | 0.5 |
| Voltage (Nom) | 220-240 V |
| Inrush current at mains | 26 |
| Max. lamp no. on MCB B type 10A - Mains | 7 |
| Max. lamp no. on MCB B type 10A – EM ballast | - |
| without Comp. Cap. | |
| Max. lamp no. on MCB B type 10A – EM ballast | - |
| with Comp. Cap. | |
| Max. lamp no. on MCB B type 16A - Mains | 12 |
| Max. lamp no. on MCB B type 16A – EM ballast | - |
| without Comp. Cap. | |
| Max. lamp no. on MCB B type 16A – EM ballast | - |
| with Comp. Cap. | |
| Ballast Compatibility | Mains |
| | |
| Temperature | |
| Ambient temperature range | -30 to +45 °C |
| T-Case Maximum (Nom) | 50.4 °C |
| | |
| Controls and Dimming | |
| Dimmable | No |
| | |


| Mechanical and Housing | |
|---------------------------------|---------------------------------|
| Bulb Finish | Frosted |
| Bulb Shape | ED75 |
| | |
| Approval and Application | |
| Energy Efficiency Class | D |
| Energy Consumption kWh/1000 h | 18 kWh |
| EPREL Registration Number | 1617391 |
| | |
| Product Data | |
| Order product name | TForce Core LED HPL 18W E27 827 |
| | FR |
| Full product name | TForce Core LED HPL 18W E27 827 |
| | FR |
| Full product code | 872016926779400 |
| Order code | 929003731202 |
| Material Nr. (12NC) | 929003731202 |
| Numerator - Quantity Per Pack | 1 |
| EAN/UPC - Product/Case | 8720169267794 |
| Numerator - Packs per outer box | 6 |
| EAN/UPC - Case | 8720169267800 |
| · | |


Dimensional drawing



| Product | D | С |
|------------------------------------|-------|--------|
| TForce Core LED HPL 18W E27 827 FR | 76 mm | 183 mm |

Photometric data






Calculat Reconnector 45 Philips Lighting SLV. Page: 111


Light Distribution Diagram - TForce Core LED HPL 18W E27 827 FR


General uniform lighting - TForce Core LED HPL 18W E27 827 FR



Spectral Power Distribution Colour - TForce Core LED HPL 18W E27 827 FR

Lifetime





Life Expectancy Diagram - TForce Core LED HPL 18W E27 827 FR

Lumen Maintenance Diagram - TForce Core LED HPL 18W E27 827 FR



© 2024 Signify Holding All rights reserved. Signify does not give any representation or warranty as to the accuracy or completeness of the information included herein and shall not be liable for any action in reliance thereon. The information presented in this document is not intended as any commercial offer and does not form part of any quotation or contract, unless otherwise agreed by Signify. Philips and the Philips Shield Emblem are registered trademarks of Koninklijke Philips N.V.