

Product Datasheet Date: 22/09/2012

Metal Halide Lamp with Quartz Burner HRI-TS 250W/WDL/230/FC2

Logistic Data

Article No.	32418890
Code	HRI-TS 250W/WDL/230/FC2
Product EAN	4008597188909
Customs tariff no.	85393290
Box quantitiy (pcs.)	12
EAN Box	4008597488900
Gross weight of box in kg	1.5
Length of box in m	0.27
Width of box in m	0.22
Height of box in m	0.29
Pieces per palett	1020
ETIM Class	EC000037
ETIM class name	Metal halide lamp without reflector



Electric Parameters

Lamp nominal wattage	250 W
Rated wattage	250.0 W

Light Application Parameters

Luminous flux	22000 lm
Luminous efficiency	88 lm/W
Colour temperature	3200 K
Colour rendering index Ra	80

Service Life


Mean service life	12000 h
Info about service life	12B50, 50Hz

Specification

Diameter max.	26 mm
Length max.	162 mm

Miscellaneous


ILCOS name	MD/UB-250/832-H-Fc2
LBS name	HIT-DE-h45 250W/832 Fc2





Notes

Base



Fc2 IEC/EN 60061-1 sheet 7004-114-1

Spectrum

daylight(D 65)

General notes

The technical design data in accordance with DIN and IEC. The producer does not take any responsibility for damage to persons or property in case of unsuitable operation or handling of the product. Operating data and dimensions are valid within the usual tolerances. Related lamp types (different bases, mains voltages) may be available on request. Sale and delivery are effected in accordance with the Radium Terms of Delivery and Payment valid on the day of conclusion of contract. Packing units offer economical advantages to the purchase and logistic department. Please match your quantity volume accordingly. For orders of a minimum quantity (clefts) with a lamp model the amount lower than the volume of each packaging unit, we will invoice 10 % additional charge per lamp type. Technical changes and terms of delivery are reserved. Manipulation of any kind to packaging or product is not permissible as this will violate Radium brand rights. Furthermore, technical properties of the product can change to its disadvantage or even destruction. Therefore, Radium cannot be responsible for consequential damages. Subject to change without notice. Errors and omissions excepted. (B) = Registered trademark

All technical data without guarantee.